

DIGIMIC DSwitch

Backup Switchover Unit

Article no.: 05.0040



Description

The DIGIMIC DSwitch backup switchover unit provides improved system reliability by backing up all connected DCen central units within the DIGIMIC conference system (A/B Switch). In case of a failure the DSwitch can switch over from the main DCen to the backup unit either by a button press on the DSwitch front or via a software command. Up to four DCens can be connected to one DSwitch forming a DCen cluster which can be switched over individually or simultaneously.

The brählerOS software application can detect possible failures and starts the switch over process accordingly by the operator's command. The brählerOS software will continue operating with the backup DCen and the connected units.

The current switching status as well as the correct power supply of each individual microphone chain is indicated by coloured LEDs on the front.

Features

- Dual 4 line switchover unit
- 2 separate switching circuits
- Software controlled switchover
- Separate line power indicators
- Coloured status indicator
- 2x 4+4 RJ45 DCen inputs
- 2x 4 RJ45 DIGIMIC outputs
- 1x RJ45 LAN connector

Power Supply

- 90 – 240 VAC, 16W

Housing

- 19", 2 HU, Aluminium, front: "grey" painted back: "silver" anodized
- W x H x D: (433 x 88 x 330)mm approx. (17.0 x 3.5 x 13.0) inch (without mounting brackets)

System requirements

System Software

- Requires either Single Conference License, Article-No.: OS.0100
- or
- Multi Conference License, Article-No.: OS.1000

Supported Central Control Units

- DCen (8 audio channels) Article no.: 05.0010
- DCen32 (32 audio channels) Article no.: 05.0050